

PRODUCT DATA SHEET · EN

FOS 24ch DMX console


DMX fader controller, 24 channels

DMX controller with 24 fader-operated channels in two banks, PRESET A and PRESET B. It lets you record, edit and run scene programs.

24	3-pin XLR	DC 12-18 V	4.8 kg
CHANNELS	DMX OUTPUT	POWER INPUT	WEIGHT

Key features

- Faders and FLASH buttons for channels 1-12 (PRESET A) and 13-24 (PRESET B)
- MASTER A, MASTER B, FADE TIME and SPEED faders, TAP SYNC button for setting the chase speed
- Program recording and scene editing, including deleting, adding and modifying steps
- Audio mode for chases, AUDIO LEVEL fader for adjusting the audio input sensitivity
- FULL ON and BLACK OUT buttons, both functions also remotely controllable via a 1/4" stereo jack
- MIDI IN, OUT and THRU connectors, data dump sending and receiving, DMX output polarity selection



Rear panel

1 power input
2 MIDI THRU
3 MIDI OUT
4 MIDI IN
5 DMX output
6 DMX polarity selector
7 audio input
8 remote control

Manufacturer's drawing

Technical data

Number of channels	24
Power input	DC 12-18 V, 500 mA
Power supply	AC 230 V 50 Hz, DC 12 V, 500 mA
DMX output	3-pin female XLR
MIDI connectors	5-pin DIN
Audio input (line)	100 mV-1 Vpp
Remote control	1/4" stereo jack
Fuse (internal)	F0.5 A 250 V, 5 × 20 mm
Dimensions	482 × 264 × 85 mm
Weight	4.8 kg

Documentation

User manual PL and original EN
on the product page →

Manufacturer's original manual
EN, fos-lighting.eu →

⚠ **Read the entire user manual and follow the safety rules before using the device.**

Manufacturer and distributor

MANUFACTURER

FOS Technologies LTD

Bulevard Iliensko Shose 8, Sladova Baza ZMM
Sofia, Bulgaria
info@fos-lighting.eu · www.fos-lighting.eu

DISTRIBUTOR IN POLAND

VEX Systems

Media Rental Oleksandr Zakariya
al. Niepodległości 20/55, 02-653 Warszawa, Poland
NIP 5214048857 · +48 794 797 959
biuro@vex-systems.pl · vex-systems.pl