

PRODUCT DATA SHEET · EN

FOS COB System

RGBW COB LED Par system

LED Par system with 4 COB LEDs of 30 W each, 4-in-1 RGBW, every LED controlled individually. Power consumption 150 W, beam angle 25°.

150 W	4 × 30 W	25°	4.67 kg
POWER CONSUMPTION	COB LEDS	BEAM ANGLE	NET WEIGHT

Key features

- 4-in-1 RGBW colour, each LED controlled individually
- Control: DMX, master-slave, auto run and remote mode
- DMX channel modes: 4, 6, 16 and 25 channels
- Built-in programmes and adjustable dimming speed
- 3-pin XLR DMX sockets (female and male) and PowerCON In/Out power connectors
- LED display on the panel and black aluminium housing

Technical data

Power supply	100-256 V AC 50-60 Hz
Power consumption	150 W
LEDs	4 COB LEDs, 30 W each
Colour	4-in-1 RGBW
Beam angle	25°
Channel modes	4/6/16/25 CH
DMX sockets	3-pin XLR, female and male
Power IN/OUT	PowerCON In/Out
Ambient temperature	from -15 °C to 40 °C
To flammable materials	min. 1 m
Net weight	4.67 kg

Documentation

User manual PL and original EN
on the product page →

Manufacturer's original manual
EN, fos-lighting.eu →

> ⚠ **Read the entire user manual and follow the safety rules before using the fixture.**

Manufacturer and distributor

MANUFACTURER

FOS Technologies LTD

Bulevard Iliensko Shose 8, Sladova Baza ZMM
Sofia, Bulgaria
info@fos-lighting.eu · www.fos-lighting.eu

DISTRIBUTOR IN POLAND

VEX Systems

Media Rental Oleksandr Zakariya
al. Niepodległości 20/55, 02-653 Warszawa, Poland
NIP 5214048857 · +48 794 797 959
biuro@vex-systems.pl · vex-systems.pl