

PRODUCT DATA SHEET · EN

Gigband Transmitter

BLE/DMX transmitter for LED wristbands

BLE/DMX transmitter for LED wristbands, controlled from the RF Fun app or a DMX controller. 41 DMX512 channels, Bluetooth range up to 8 m.

41	up to 8 m	10	5
DMX512 CHANNELS	BLUETOOTH RANGE	ZONES	BUTTONS

Key features

- Bluetooth control from the RF Fun app: one zone, several zones or all zones
- Colour modes: Sparkles, RGB Fade, RGB Blink, Blink Moving, Fade Moving
- DMX mode switched in the app or with button 5 on the transmitter panel
- 5-pin and 3-pin DMX inputs and an audio input
- BLE firmware update from within the app
- Separate RF and BLE antennas, 6 V / 1 A power supply

Technical data

DMX channels	41 (DMX512)
Bluetooth range	up to 26 ft (approx. 8 m)
Control zones	10
Power supply	DC socket 6 V / 1 A
DMX inputs	5-pin and 3-pin
Audio input	AUDIO IN
Antennas	RF ANTENNA and BLE ANTENNA
App	RF Fun (iOS, Android)

Documentation

User manual PL and original EN
on the product page →

Manufacturer's original manual
EN, fos-lighting.eu →

⚠ **Read the whole user manual before using the transmitter and follow the safety rules.**

Manufacturer and distributor

MANUFACTURER

FOS Technologies LTD

Bulevard Iliensko Shose 8, Sladova Baza ZMM
Sofia, Bulgaria
info@fos-lighting.eu · www.fos-lighting.eu

DISTRIBUTOR IN POLAND

VEX Systems

Media Rental Oleksandr Zakariya
al. Niepodległości 20/55, 02-653 Warszawa, Poland
NIP 5214048857 · +48 794 797 959
biuro@vex-systems.pl · vex-systems.pl