

PRODUCT DATA SHEET · EN

FOS 18 DMX Console


18-channel DMX console

Compact DMX console with 18 fader-controlled channels over 3 pages and a display of the selected channel and DMX value. Weighs 1.1 kg.

18	3	6 + master	1.1 kg
DMX CHANNELS	PAGES	FADERS	WEIGHT

Key features

- 18 fader-controlled channels: 6 faders and a master dimmer, 3 pages
- Display of the selected channel and DMX value
- USB port for a wireless DMX transmitter (not included)
- Signal output: 3-pin female XLR
- Powered by 5 V DC (USB Type-C) or a 9 V battery, power supply included
- Compact design, simple operation



Device layout

Rear 9 V battery, On/Off, USB-C, DMX Out, USB

Top Page button, channel, DMX value

Manufacturer's drawing, EN labels

Technical data

DMX channels	18 (3 pages)
Faders	6 + 1 master dimmer
Display	selected channel and DMX value
Signal output	3-pin female XLR
Power supply	5 V DC (USB Type-C) or 9 V battery
USB port	for a wireless DMX transmitter
Power adapter	included
Dimensions	240 × 140 × 65 mm
Weight	1.1 kg

Documentation

User manual PL and original EN
on the product page →

Manufacturer's original manual
EN, fos-lighting.eu →

Read the entire user manual before use and follow the safety instructions.

Manufacturer and distributor

MANUFACTURER

FOS Technologies LTD

Bulevard Iliensko Shose 8, Sladova Baza ZMM
Sofia, Bulgaria
info@fos-lighting.eu · www.fos-lighting.eu

DISTRIBUTOR IN POLAND

VEX Systems

Media Rental Oleksandr Zakariya
al. Niepodległości 20/55, 02-653 Warszawa, Poland
NIP 5214048857 · +48 794 797 959
biuro@vex-systems.pl · vex-systems.pl